

ZyXEL Prestige 2000W – Configurazione

Per configurare il Telefono VoIP Wi-Fi ZyXEL Prestige 2000W seguire le seguenti semplici istruzioni.

Dopo aver caricato la batteria interna per un tempo sufficiente, individuare l'indirizzo IP attribuito dal server DHCP della rete e accedere all'interfaccia web del telefonino con la login zyxeladmin e la password di default 1234

Menu Network

The screenshot shows the ZyXEL VoIP Phone Web Configuration interface in Microsoft Internet Explorer. The browser address bar shows the URL `http://192.168.1.105/index.htm`. The page title is "ZyXEL VoIP Phone Web Configuration - Microsoft Internet Explorer". The interface features a blue header with the ZyXEL logo and a navigation menu on the left. The main content area is titled "NETWORK CONFIGURATION" and displays various network settings with input fields and buttons.

Parameter	Value
Get IP Address	<input type="radio"/> STATIC <input checked="" type="radio"/> DHCP <input type="radio"/> PPPoE
Network Mode	DHCP
Network IP	192.168.1.105
Network Subnet Mask	255.255.255.0
Default Gateway	192.168.1.1
MAC Address	00a0c5b7653d
DNS Server IP	<input type="text" value="194.243.154.62"/>
Second DNS Server IP	<input type="text" value="195.31.190.31"/>

Buttons:

Left navigation menu:

- [Information](#)
- [Network](#)
- [SIP](#)
- [NAT TRVSL](#)
- [PHONE](#)
- [PHONE BOOK](#)
- [Wireless](#)
- [TOS/DS](#)
- [System](#)
- [S/W Update](#)

Buttons:

Menu SIP

The screenshot displays the ZyXEL VoIP Phone Web Configuration interface within a Microsoft Internet Explorer browser window. The browser's address bar shows the URL `http://192.168.1.105/index.htm`. The page features a blue header with the ZyXEL logo and a left-hand navigation menu with links for Information, Network, SIP, NAT TRVSL, PHONE, PHONE BOOK, Wireless, TOS/DS, System, and S/W Update. A 'RESTART' button is located below the menu.

The main content area is titled 'SIP URI' and contains the following configuration fields:

- SIP URI: sip: 03761855101 @ voip.eutelia.it : 5060
- SIP Server Address: voip.eutelia.it
- SIP Server Port: 5060
- Registrar Server Address: voip.eutelia.it
- Registrar Server Port: 5060
- Register Expiry Time(sec.): 300
- OPTIONS Interval Timer: 0
- Session Expiry Time(sec.): 0
- Display Name: 03761855101

Below the SIP URI section is the 'Authentication' section, which includes:

- Registrar Username: 03761855101
- Registrar Password: [REDACTED]

The 'Registration Status' section shows the phone is 'Registered'. At the bottom of the configuration area, there are 'APPLY' and 'CANCEL' buttons.

The browser's status bar at the bottom indicates 'Operazione completata' (Operation completed) and 'Internet'.

Menu NAT TRVSL

ZyXEL
TOTAL INTERNET ACCESS SOLUTION

[Information](#)
[Network](#)
[SIP](#)
[NAT TRVSL](#)
[PHONE](#)
[PHONE BOOK](#)
[Wireless](#)
[TOS/DS](#)
[System](#)
[S/W Update](#)

RESTART

NAT TRAVERSAL

Select Type: STUN (RFC3489)

Outbound Proxy

Outbound Proxy Server Address:

Outbound Proxy Server Port:

STUN (RFC3489)

STUN Server IP: :

STUN Interval(sec.):

Fake WAN Address on SIP and RTP

WAN IP Address:

Operazione completata

Internet

Menu Phone

ZyXEL
TOTAL INTERNET ACCESS SOLUTION

[Information](#)
[Network](#)
[SIP](#)
[NAT TRVSL](#)
[PHONE](#)
[PHONE BOOK](#)
[Wireless](#)
[TOS/DS](#)
[System](#)
[S/W Update](#)

PHONE SETTINGS

Default Voice Codec: G.729, 8k

Speaking Volume(-14~14): 5

Listening Volume(-14~14): -5

RTP Port: 13456

Jitter Buffer: Small Medium Large

Voice Frames per Packet: Small Medium Large

DTMF Relay: inband(RFC2833)

DTMF Payload(0~127): 18

Operazione completata

Rilevata password